

CVS/Caremark

Implementation Guide

850 – DC Purchase Order

Version X12-4010

Table of Contents

850	Purchase Order	1
ISA	Interchange Control Header	3
GS	Functional Group Header	5
ST	Transaction Set Header	7
BEG	Beginning Segment for Purchase Order	8
REF	Reference Information	9
PER	Administrative Communications Contact	10
SAC	Loop Service, Promotion, Allowance, or Charge Information	11
SAC	Service, Promotion, Allowance, or Charge Information	12
ITD	Terms of Sale/Deferred Terms of Sale	14
DTM	Date/Time Reference	15
AMT	Loop Monetary Amount Information	16
AMT	Monetary Amount Information	17
N9	Loop Reference Identification	18
N9	Reference Identification	19
MSG	Message Text	20
N1	Loop Party Identification	21
N1	Party Identification	22
N3	Party Location	23
N4	Geographic Location	24
PO1	Loop Baseline Item Data	25
PO1	Baseline Item Data	26
PAM	Period Amount	28
PID	Product/Item Description	29
PO4	Item Physical Details	31
CTT	Loop Transaction Totals	32
CTT	Transaction Totals	33
SE	Transaction Set Trailer	34
GE	Functional Group Trailer	35
IEA	Interchange Control Trailer	36

850

Purchase Order

Functional Group=PO

Purpose: This Draft Standard for Trial Use contains the format and establishes the data contents of the Purchase Order Transaction Set (850) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to the placement of purchase orders for goods and services. This transaction set should not be used to convey purchase order changes or purchase order acknowledgment information.

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	ST	Transaction Set Header	M	1			Must use
020	BEG	Beginning Segment for Purchase Order	M	1			Must use
050	REF	Reference Information	O	>1			Must use
060	PER	Administrative Communications Contact	O	3			Must use
LOOP ID - SAC					25		
120	SAC	Service, Promotion, Allowance, or Charge Information	O	1			Must use
130	ITD	Terms of Sale/Deferred Terms of Sale	O	>1			Must use
150	DTM	Date/Time Reference	O	10			Must use
LOOP ID - AMT					>1		
287	AMT	Monetary Amount Information	O	1			Must use
LOOP ID - N9					1000		
295	N9	Reference Identification	M	1			Must use
300	MSG	Message Text	O	1000			Must use
LOOP ID - N1					200		
310	N1	Party Identification	O	1			Must use
330	N3	Party Location	O	2			Used
340	N4	Geographic Location	O	>1			Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - PO1					100000	N2/0100L	
010	PO1	Baseline Item Data	M	1		N2/0100	Must use
045	PAM	Period Amount	O	10			Must use
090	PO4	Item Physical Details	O	>1			Must use

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - CTT					1	N3/0100L	
010	CTT	Transaction Totals	O	1		N3/0100	Must use
030	SE	Transaction Set Trailer	M	1			Must use

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

Notes:

2/0100L PO102 is required.

2/0100 PO102 is required.

3/0100L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

3/0100 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

Purpose: To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier	M	ID	2/2	Must use

Description: Code identifying the type of information in the Authorization Information

CodeList Summary (Total Codes: 7, Included: 1)

<u>Code</u>	<u>Name</u>
00	No Authorization Information Present (No Meaningful Information in I02)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA02	I02	Authorization Information	M	AN	10/10	Must use

Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)

ISA03	I03	Security Information Qualifier	M	ID	2/2	Must use
-------	-----	--------------------------------	---	----	-----	----------

Description: Code identifying the type of information in the Security Information

CodeList Summary (Total Codes: 2, Included: 1)

<u>Code</u>	<u>Name</u>
00	No Security Information Present (No Meaningful Information in I04)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA04	I04	Security Information	M	AN	10/10	Must use

Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)

ISA05	I05	Interchange ID Qualifier	M	ID	2/2	Must use
-------	-----	--------------------------	---	----	-----	----------

Description: Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified

CodeList Summary (Total Codes: 41, Included: 1)

<u>Code</u>	<u>Name</u>
ZZ	Mutually Defined

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA06	I06	Interchange Sender ID	M	AN	15/15	Must use

Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element

ISA07	I05	Interchange ID Qualifier	M	ID	2/2	Must use
-------	-----	--------------------------	---	----	-----	----------

Description: Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified

CodeList Summary (Total Codes: 41, Included: 1)

<u>Code</u>	<u>Name</u>
08	UCC EDI Communications ID (Comm ID)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA08	I07	Interchange Receiver ID	M	AN	15/15	Must use

Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route

data to them

ISA09 I08 **Interchange Date** M DT 6/6 Must use

Description: Date of the interchange

ISA10 I09 **Interchange Time** M TM 4/4 Must use

Description: Time of the interchange

ISA11 I65 **Repetition Separator** M 1/1 Must use

Description: Type is not applicable; the repetition separator is a delimiter and not a data element; this field provides the delimiter used to separate repeated occurrences of a simple data element or a composite data structure; this value must be different than the data element separator, component element separator, and the segment terminator

ISA12 I11 **Interchange Control Version Number** M ID 5/5 Must use

Description: Code specifying the version number of the interchange control segments

CodeList Summary (Total Codes: 20, Included: 1)

<u>Code</u>	<u>Name</u>
00401	Draft Standards for Trial Use Approved for Publication by ASC X12 Procedures Review Board through October 1997

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA13	I12	Interchange Control Number	M	N0	9/9	Must use

Description: A control number assigned by the interchange sender

ISA14 I13 **Acknowledgment Requested** M ID 1/1 Must use

Description: Code indicating sender's request for an interchange acknowledgment

CodeList Summary (Total Codes: 2, Included: 1)

<u>Code</u>	<u>Name</u>
0	No Interchange Acknowledgment Requested

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA15	I14	Interchange Usage Indicator	M	ID	1/1	Must use

Description: Code indicating whether data enclosed by this interchange envelope is test, production or information

CodeList Summary (Total Codes: 3, Included: 1)

<u>Code</u>	<u>Name</u>
P	Production Data

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA16	I15	Component Element Separator	M		1/1	Must use

Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator

GS

Functional Group Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use

Purpose: To indicate the beginning of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	Functional Identifier Code	M	ID	2/2	Must use

Description: Code identifying a group of application related transaction sets

CodeList Summary (Total Codes: 260, Included: 1)

<u>Code</u>	<u>Name</u>
PO	Purchase Order (850)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS02	142	Application Sender's Code	M	AN	2/15	Must use

Description: Code identifying party sending transmission; codes agreed to by trading partners

GS03	124	Application Receiver's Code	M	AN	2/15	Must use
------	-----	-----------------------------	---	----	------	----------

Description: Code identifying party receiving transmission; codes agreed to by trading partners

GS04	373	Date	M	DT	8/8	Must use
------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

GS05	337	Time	M	TM	4/8	Must use
------	-----	------	---	----	-----	----------

Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)

GS06	28	Group Control Number	M	N0	1/9	Must use
------	----	----------------------	---	----	-----	----------

Description: Assigned number originated and maintained by the sender

GS07	455	Responsible Agency Code	M	ID	1/2	Must use
------	-----	-------------------------	---	----	-----	----------

Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480

CodeList Summary (Total Codes: 2, Included: 1)

<u>Code</u>	<u>Name</u>
X	Accredited Standards Committee X12

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use

Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed

CodeList Summary (Total Codes: 54, Included: 1)

<u>Code</u>	<u>Name</u>
004010	Draft Standards Approved for Publication by ASC X12 Procedures Review Board through October 1997

Semantics:

- GS04 is the group date.

2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use

Description: Code uniquely identifying a Transaction Set

CodeList Summary (Total Codes: 318, Included: 1)

<u>Code</u>	<u>Name</u>
850	Purchase Order

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST02	329	Transaction Set Control Number	M	AN	4/9	Must use

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.

BEG Beginning Segment for Purchase Order

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 4

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BEG01	353	Transaction Set Purpose Code	M	ID	2/2	Must use

Description: Code identifying purpose of transaction set

CodeList Summary (Total Codes: 66, Included: 1)

<u>Code</u>	<u>Name</u>
00	Original

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BEG02	92	Purchase Order Type Code	M	ID	2/2	Must use

Description: Code specifying the type of Purchase Order

CodeList Summary (Total Codes: 76, Included: 1)

<u>Code</u>	<u>Name</u>
SA	Stand-alone Order

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BEG03	324	Purchase Order Number	M	AN	1/22	Must use

Description: Identifying number for Purchase Order assigned by the orderer/purchaser

BEG05	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Semantics:

1. BEG05 is the date assigned by the purchaser to purchase order.

REF Reference Information

Pos: 0500	Max: >1
Heading - Optional	
Loop: N/A	Elements: 3

User Option (Usage): Must use
Purpose: To specify identifying information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1731, Included: 2)

<u>Code</u>	<u>Name</u>
VR	Vendor ID Number
ZZ	Mutually Defined

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF02	127	Reference Identification	X	AN	1/50	Used

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

Vendor Number assigned by CVS

REF03	352	Description	X	AN	1/80	Used
-------	-----	-------------	---	----	------	------

Description: A free-form description to clarify the related data elements and their content

PO Comment – must be reviewed
 Promotional Data, Seasonal Promotion Code, or any information to better define this order

No receiving from mm/dd/yy to mm/dd/yy

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

PER Administrative Communications Contact

Pos: 0600	Max: 3
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To identify a person or office to whom administrative communications should be directed

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PER01	366	Contact Function Code	M	ID	2/2	Must use

Description: Code identifying the major duty or responsibility of the person or group named

CodeList Summary (Total Codes: 238, Included: 1)

<u>Code</u>	<u>Name</u>
BD	Buyer Name or Department

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PER02	93	Name	O	AN	1/60	Must use

Description: Free-form name

Buyer Name

Syntax Rules:

1. P0304 - If either PER03 or PER04 is present, then the other is required.
2. P0506 - If either PER05 or PER06 is present, then the other is required.
3. P0708 - If either PER07 or PER08 is present, then the other is required.

Loop Service, Promotion, Allowance, or Charge Information

Pos: 1200	Repeat: 25
Optional	
Loop: SAC	Elements: N/A

User Option (Usage): Used

Purpose: To request or identify a service, promotion, allowance, or charge; to specify the amount or percentage for the service, promotion, allowance, or charge

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
1200	SAC	Service, Promotion, Allowance, or Charge Information	O	1		Must use

SAC Service, Promotion, Allowance, or Charge Information

Pos: 1200	Max: 1
Heading - Optional	
Loop: SAC	Elements: 8

User Option (Usage): Must use

Purpose: To request or identify a service, promotion, allowance, or charge; to specify the amount or percentage for the service, promotion, allowance, or charge

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SAC01	248	Allowance or Charge Indicator	M	ID	1/1	Must use

Description: Code which indicates an allowance or charge for the service specified

CodeList Summary (Total Codes: 7, Included: 1)

<u>Code</u>	<u>Name</u>
A	Allowance

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SAC02	1300	Service, Promotion, Allowance, or Charge Code	X	ID	4/4	Must use

Description: Code identifying the service, promotion, allowance, or charge

CodeList Summary (Total Codes: 1090, Included: 2)

<u>Code</u>	<u>Name</u>
F800	Promo
C320	Display
A260	Ad
F050	Other
F910	Qty. Allowance
I310	Truckload
ZZZZ	Additional

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SAC03	559	Agency Qualifier Code	X	ID	2/2	Must use

Description: Code identifying the agency assigning the code values

CodeList Summary (Total Codes: 194, Included: 1)

<u>Code</u>	<u>Name</u>
ZZ	Mutually Defined

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SAC04	1301	Agency Service, Promotion, Allowance, or Charge Code	X	AN	1/10	Must use

Description: Agency maintained code identifying the service, promotion, allowance, or charge

ZZ - Mutually Defined

SAC06	378	Allowance/Charge Percent Qualifier	X	ID	1/1	Must use
-------	-----	------------------------------------	---	----	-----	----------

Description: Code indicating on what basis allowance or charge percent is calculated

CodeList Summary (Total Codes: 16, Included: 1)

<u>Code</u>	<u>Name</u>
I	Item List Cost

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SAC07	332	Percent, Decimal Format	X	R	1/6	Must use

Description: Percent given in decimal format (e.g., 0.0 through 100.0 represents 0% through 100%)

SAC12 331 **Allowance or Charge Method of Handling Code** O ID 2/2 Must use

Description: Code indicating method of handling for an allowance or charge

CodeList Summary (Total Codes: 22, Included: 1)

<u>Code</u>	<u>Name</u>
01	Bill Back
02	Off-Invoice
06	Charge to be Paid by Customer

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SAC15	352	Description	X	AN	1/80	Must use

Description: A free-form description to clarify the related data elements and their content

- Promo
- Display
- Ad
- Other
- Quantity Allowance
- Truckload
- Carload
- Backhaul
- Additional

Syntax Rules:

1. R0203 - At least one of SAC02 or SAC03 is required.
2. P0304 - If either SAC03 or SAC04 is present, then the other is required.
3. P0607 - If either SAC06 or SAC07 is present, then the other is required.
4. P0910 - If either SAC09 or SAC10 is present, then the other is required.
5. C1110 - If SAC11 is present, then SAC10 is required.
6. C1413 - If SAC14 is present, then SAC13 is required.
7. C1615 - If SAC16 is present, then SAC15 is required.

Semantics:

1. If SAC01 is "A" or "C", then at least one of SAC05, SAC07, or SAC08 is required.
2. SAC05 is the total amount for the service, promotion, allowance, or charge.
3. If SAC05 is present with SAC07 or SAC08, then SAC05 takes precedence.
4. SAC08 is the allowance or charge rate per unit.
5. SAC10 and SAC11 is the quantity basis when the allowance or charge quantity is different from the purchase order or invoice quantity.
6. SAC10 and SAC11 used together indicate a quantity range, which could be a dollar amount, that is applicable to service, promotion, allowance, or charge.
7. SAC13 is used in conjunction with SAC02 or SAC04 to provide a specific reference number as identified by the code used.
8. SAC14 is used in conjunction with SAC13 to identify an option when there is more than one option of the promotion.
9. SAC16 is used to identify the language being used in SAC15.

Comments:

1. SAC04 may be used to uniquely identify the service, promotion, allowance, or charge. In addition, it may be used in conjunction with SAC03 to further define SAC02.
2. In some business applications, it is necessary to advise the trading partner of the actual dollar amount that a particular allowance, charge, or promotion was based on to reduce ambiguity. This amount is commonly referred to as "Dollar Basis Amount". It is represented in the SAC segment in SAC10 using the qualifier "DO" - Dollars in SAC09.

ITD Terms of Sale/Deferred Terms of Sale

Pos: 1300	Max: >1
Heading - Optional	
Loop: N/A	Elements: 6

User Option (Usage): Must use

Purpose: To specify terms of sale

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ITD01	336	Terms Type Code	O	ID	2/2	Must use

Description: Code identifying type of payment terms

CodeList Summary (Total Codes: 77, Included: 1)

<u>Code</u>	<u>Name</u>
01	Basic
02	EOM
04	Deferred or Installment
07	Extended

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ITD02	333	Terms Basis Date Code	O	ID	1/2	Must use

Description: Code identifying the beginning of the terms period

CodeList Summary (Total Codes: 17, Included: 1)

<u>Code</u>	<u>Name</u>
15	Receipt of Goods
4	Specified Date

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ITD03	338	Terms Discount Percent	O	R	1/6	Used

Description: Terms discount percentage, expressed as a percent, available to the purchaser if an invoice is paid on or before the Terms Discount Due Date

ITD05	351	Terms Discount Days Due	X	N0	1/3	Used
-------	-----	-------------------------	---	----	-----	------

Description: Number of days in the terms discount period by which payment is due if terms discount is earned

ITD07	386	Terms Net Days	O	N0	1/3	Used
-------	-----	----------------	---	----	-----	------

Description: Number of days until total invoice amount is due (discount not applicable)

ITD10	389	Deferred Amount Due	X	N2	1/10	Used
-------	-----	---------------------	---	----	------	------

Description: Deferred amount due for payment.

Please Ignore. Will always be a 1

Syntax Rules:

- 1.L03040513 - If ITD03 is present, then at least one of ITD04, ITD05 or ITD13 is required.
- 2.L08040513 - If ITD08 is present, then at least one of ITD04, ITD05 or ITD13 is required.
- 3.L091011 - If ITD09 is present, then at least one of ITD10 or ITD11 is required.

Semantics:

- 1.ITD15 is the percentage applied to a base amount used to determine a late payment charge.

Comments:

- 1.If the code in ITD01 is "04", then ITD07 or ITD09 is required and either ITD10 or ITD11 is required; if the code in ITD01 is "05", then ITD06 or ITD07 is required.

DTM Date/Time Reference

Pos: 1500	Max: 10
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Must use
Purpose: To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use

Description: Code specifying type of date or time, or both date and time

CodeList Summary (Total Codes: 1280, Included: 1)

<u>Code</u>	<u>Name</u>
002	Delivery Requested

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM02	373	Date	X	DT	8/8	Must use

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Delivery by Date(CCYYMMDD)

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

Loop Monetary Amount Information

Pos: 2870	Repeat: >1
	Optional
Loop: AMT	Elements: N/A

User Option (Usage): Must use

Purpose: To indicate the total monetary amount

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2870	AMT	Monetary Amount Information	O	1		Must use

AMT Monetary Amount Information

Pos: 2870	Max: 1
Heading - Optional	
Loop: AMT	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the total monetary amount

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
AMT01	522	Amount Qualifier Code	M	ID	1/3	Must use

Description: Code to qualify amount

CodeList Summary (Total Codes: 1765, Included: 1)

<u>Code</u>	<u>Name</u>
BAP	Total Amount Due

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
AMT02	782	Monetary Amount	M	R	1/18	Must use

Description: Monetary amount

Total PO Dollar Amount (Informational only, not required)

Loop Reference Identification

Pos: 2950	Repeat: 1
Mandatory	
Loop: N9	Elements: N/A

User Option (Usage): Must use

Purpose: To indicate the Reference Identification

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2950	N9	Reference Identification	M	1		Must use

N9

Reference Identification

Pos: 2950	Max: 1
Heading - Optional	
Loop: N9	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the Reference Identification

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1765, Included: 1)

<u>Code</u>	<u>Name</u>
L1	Letters or Notes

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N902	127	Reference Identification	O	AN	1/30	Must use

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

PO COMMENTS

MSG Message Text

Pos: 3000	Max: 1000
Heading - Optional	
Loop: N9	Elements: 1

User Option (Usage): Must use

Purpose: To provide a free-form format that allows the transmission of text information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MSG01	933	Free-Form Message Text	M	AN	1/264	Must use

Description: Free-form message text

Loop Party Identification

Pos: 3100	Repeat: 200
	Optional
Loop: N1	Elements: N/A

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3100	N1	Party Identification	O	1		Must use
3300	N3	Party Location	O	2		Used
3400	N4	Geographic Location	O	>1		Used

N1

Party Identification

Pos: 3100	Max: 1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

CodeList Summary (Total Codes: 1500, Included: 1)

<u>Code</u>	<u>Name</u>
ST	Ship To
OT	Origin Terminal

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N103	66	Identification Code Qualifier	X	ID	1/2	Must use

Description: Code designating the system/method of code structure used for Identification Code (67)

CodeList Summary (Total Codes: 241, Included: 1)

<u>Code</u>	<u>Name</u>
54	Warehouse (Use if Front Store OTC Items)
11	Use if Pharmacy (DEA Number)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N104	67	Identification Code	X	AN	2/80	Must use

Description: Code identifying a party or other code

If N103 = '54' - 4 Character Warehouse Code (See Distribution Center ID Table for Ship-to-location)

If N103 = '11' - (See DEA Codes Table for Ship-to-location)

If N101 = 'OT' - (FOB Point- for imports only)

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3

Party Location

Pos: 3300	Max: 2
Heading - Optional	
Loop: N1	Elements: 1

User Option (Usage): Used

Purpose: To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use
		Description: Address information				
		Address information				

N4

Geographic Location

Pos: 3400	Max: >1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Must use
		Description: Free-form text for city name				
		<u>City Name</u>				
N402	156	State or Province Code	X	ID	2/2	Must use
		Description: Code (Standard State/Province) as defined by appropriate government agency				
		<u>State</u>				
N403	116	Postal Code	O	ID	3/15	Must use
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				
		<u>Zip Code</u>				

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Loop Baseline Item Data

Pos: 0100 Repeat: 100000
 Mandatory
 Loop: PO1 Elements: N/A

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	PO1	Baseline Item Data	M	1		Must use
0450	PAM	Period Amount	O	10		Must use
0900	PO4	Item Physical Details	O	>1		Must use

PO1 Baseline Item Data

Pos: 0100	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 9

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO102	380	Quantity	X	R	1/15	Must use

Description: Numeric value of quantity

On order Quantity

PO103	355	Unit or Basis for Measurement Code	O	ID	2/2	Must use
-------	-----	------------------------------------	---	----	-----	----------

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

CodeList Summary (Total Codes: 844, Included: 1)

<u>Code</u>	<u>Name</u>
CA	Case (If Front Store)
PC	Pieces (If RX)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO104	212	Unit Price	X	R	1/17	Must use

Description: Price per unit of product, service, commodity, etc.

If Front Store – Case Price

If RX – Unit Price

PO106	235	Product/Service ID Qualifier	X	ID	2/2	Must use
-------	-----	------------------------------	---	----	-----	----------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 1)

<u>Code</u>	<u>Name</u>
UI	U.P.C. Consumer Package Code (1-5-5)
UD	U.P.C/EAN Consumer Package Code (2-5-5)
ND	If RX – ND (NDC)
PI	If no UPC is available, will be Purchaser’s Item Number (PI)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO107	234	Product/Service ID	X	AN	1/48	Must use

Description: Identifying number for a product or service

Item UPC Number or EAN

If no UPC is available, will be Purchaser’s Item Number (6 characters)

If RX – NDC

PO108	235	Product/Service ID Qualifier	X	ID	2/2	Used
-------	-----	------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 1)

<u>Code</u>	<u>Name</u>
UA	U.P.C./EAN Case Code (2-5-5)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO109	234	Product/Service ID	X	AN	1/48	Used

Description: Identifying number for a product or service

Case UPC Code

PO110	235	Product/Service ID Qualifier	X	ID	2/2	Must use
-------	-----	-------------------------------------	---	----	-----	----------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 1)

<u>Code</u>	<u>Name</u>
PI	Purchaser's Item Code

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO111	234	Product/Service ID	X	AN	1/48	Must use

Description: Identifying number for a product or service

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Semantics:

1. PO102 is quantity ordered.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

PAM Period Amount

Pos: 0450	Max: 10
Detail - Optional	
Loop: PO1	Elements: 3

User Option (Usage): Must use

Purpose: To indicate a quantity, and/or amount for an identified period

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PAM01	673	Quantity Qualifier	X	ID	2/2	Must use

Description: Code specifying the type of quantity

CodeList Summary (Total Codes: 1123, Included: 1)

<u>Code</u>	<u>Name</u>
01	Discrete Quantity

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PAM02	380	Quantity	X	R	1/15	Must use

Description: Numeric value of quantity
Monetary Amount

PAM03	C001	Composite Unit of Measure	X	Comp		Must use
-------	------	---------------------------	---	------	--	----------

Description: To identify a composite unit of measure (See Figures Appendix for examples of use)

PAM03-01	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use
----------	-----	------------------------------------	---	----	-----	----------

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

CodeList Summary (Total Codes: 844, Included: 1)

<u>Code</u>	<u>Name</u>
ZZ	Mutually Defined

Syntax Rules:

1. P010203 - If either PAM01, PAM02 or PAM03 are present, then the others are required.
2. R020514 - At least one of PAM02, PAM05 or PAM14 is required.
3. P0405 - If either PAM04 or PAM05 is present, then the other is required.
4. L070809 - If PAM07 is present, then at least one of PAM08 or PAM09 is required.
5. C0706 - If PAM07 is present, then PAM06 is required.
6. C0807 - If PAM08 is present, then PAM07 is required.
7. C0907 - If PAM09 is present, then PAM07 is required.
8. L101112 - If PAM10 is present, then at least one of PAM11 or PAM12 is required.
9. C1007 - If PAM10 is present, then PAM07 is required.
10. C1110 - If PAM11 is present, then PAM10 is required.
11. C1210 - If PAM12 is present, then PAM10 is required.
12. P1314 - If either PAM13 or PAM14 is present, then the other is required.
13. C1505 - If PAM15 is present, then PAM05 is required.

Semantics:

1. PAM10, PAM11, or PAM12 are used when two dates are required.
2. PAM15 indicates whether the monetary amount identified in PAM05 is a net or gross value. A "Y" indicates amount is a gross value; an "N" indicates amount is a net value.

Loop Product/Item Description

Pos: 050	Repeat: 1000
	Optional
Loop: PID	Elements: N/A

User Option (Usage): Must use

Purpose: To describe a product or process in coded or free-form format

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
050	PID	Product/Item Description	O	1		Must use

PID Product/Item Description

Pos: 050	Max: 1
Detail - Optional	
Loop: PID	Elements: 2

User Option (Usage): Must use

Purpose: To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type	M	ID	1/1	Must use

Description: Code indicating the format of a description

CodeList Summary (Total Codes: 3, Included: 1)

<u>Code</u>	<u>Name</u>
F	Free-form

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID05	352	Description	X	AN	1/80	Must use

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.

PO4 Item Physical Details

Pos: 0900	Max: >1
Detail - Optional	
Loop: PO1	Elements: 1

User Option (Usage): Must use

Purpose: To specify the physical qualities, packaging, weights, and dimensions relating to the item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO401	356	Pack	O	NO	1/6	Must use

Description: The number of inner containers, or number of eaches if there are no inner containers, per outer container

Case Pack

Syntax Rules:

1. P0203 - If either PO402 or PO403 is present, then the other is required.
2. C0506 - If PO405 is present, then PO406 is required.
3. P0607 - If either PO406 or PO407 is present, then the other is required.
4. P0809 - If either PO408 or PO409 is present, then the other is required.
5. C1013 - If PO410 is present, then PO413 is required.
6. C1113 - If PO411 is present, then PO413 is required.
7. C1213 - If PO412 is present, then PO413 is required.
8. L13101112 - If PO413 is present, then at least one of PO410, PO411 or PO412 is required.
9. C1716 - If PO417 is present, then PO416 is required.
10. C1804 - If PO418 is present, then PO404 is required.

Semantics:

1. PO415 is used to indicate the relative layer of this package or range of packages within the layers of packaging. Relative Position 1 (value R1) is the innermost package.
2. PO416 is the package identifier or the beginning package identifier in a range of identifiers.
3. PO417 is the ending package identifier in a range of identifiers.
4. PO418 is the number of packages in this layer.

Comments:

1. PO403 - The "Unit or Basis for Measure Code" in this segment position is for purposes of defining the unit of measure of the "Size" identified in the PO402. For example: If the carton contains 24 12-Ounce packages, it would be described as follows: Data element 356 = "24"; Data element 357 = "12"; Data element 355 = "OZ".
2. PO413 defines the unit of measure for PO410, PO411, and PO412.

Loop Transaction Totals

Pos: 0100	Repeat: 1
Optional	
Loop: CTT	Elements: N/A

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	CTT	Transaction Totals	O	1		Must use

CTT Transaction Totals

Pos: 0100	Max: 1
Summary - Optional	
Loop: CTT	Elements: 2

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use
		Description: Total number of line items in the transaction set				
CTT02	347	Hash Total	O	R	1/10	Must use

Description: Sum of values of the specified data element. All values in the data element will be summed without regard to decimal points (explicit or implicit) or signs. Truncation will occur on the left most digits if the sum is greater than the maximum size of the hash total of the data element.
 Example: -.0018 First occurrence of value being hashed. .18 Second occurrence of value being hashed. 1.8 Third occurrence of value being hashed. 18.01 Fourth occurrence of value being hashed. 18E2 Fifth occurrence of value being hashed. ----- 1873 Hash Total

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

SE Transaction Set Trailer

Pos: 0300	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use
		Description: Total number of segments included in a transaction set including ST and SE segments				
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Comments:

1. SE is the last segment of each transaction set.

GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included	M	N0	1/6	Must use
Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element						
GE02	28	Group Control Number	M	N0	1/9	Must use
Description: Assigned number originated and maintained by the sender						

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	Number of Included Functional Groups	M	N0	1/5	Must use
		Description: A count of the number of functional groups included in an interchange				
IEA02	I12	Interchange Control Number	M	N0	9/9	Must use
		Description: A control number assigned by the interchange sender				

850 – DC Purchase Order Example v4010:

ISA*00* *00* *ZZ*CVS *01*Supplier ID *090909*1608*U*00401*000010952*0*P*^~
 GS*PO*CVSD*Supplier ID *20090909*1608*5850*X*004010~
 ST*850*179960~
 BEG*00*SA*2551146**20090825~
 REF*VR*19999~
 PER*BD*ELISA BEAN~
 SAC*A*F050*ZZ*ZZ**1* 9*****01***OTHER~
 ITD*01*15*2**25**26***100~
 DTM*002*20090901~
 AMT*BAP*86772~
 N9*L1*PO COMMENTS~
 MSG*THIS PO SUBJECT TO THE TERMS AND CONDITIONS FOUND ON CVS SUPPLIERS WEBSTE~
 N1*ST**54*I101~
 N3*2800 ENTERPRISE ST~
 N4*INDIANAPOLIS*IN*46219~
 PO1**32*CA*93.6**UI*12337001382*UA*031127001382*PI*123264~
 PAM*01*2995*ZZ~
 PO4*144~
 PO1**30*CA*131.04**UI*12337001423*UA*025137001423*PI*123269~
 PAM*01*3931*ZZ~
 PO4*12~
 PO1**40*CA*51.6**UI*12337001447*UA*012137001445*PI*123928~
 PAM*01*2064*ZZ~
 PO4*12~
 PO1**31*CA*131.04**UI*12337001584*UA*038137001584*PI*123950~
 PAM*01*4062*ZZ~
 PO4*12~
 PO1**32*CA*98.4**UI*12337001617*UA*012137001617*PI*123610~
 PAM*01*3149*ZZ~
 PO4*24~
 PO1**26*CA*98.4**UI*12337001619*UA*015137002366*PI*123609~
 PAM*01*2558*ZZ~
 PO4*24~
 PO1**18*CA*92.16**UI*12337001642*UA*023137001642*PI*123269~
 PAM*01*1659*ZZ~
 PO4*144~
 PO1**45*CA*84**UI*12337003566*UA*123137003566*PI*123688~
 PAM*01*3780*ZZ~
 PO4*24~
 PO1**52*CA*98.4**UI*12337003572***PI*123729~
 PAM*01*5117*ZZ~
 PO4*24~
 PO1**31*CA*54.24**UI*12337003657*UA*135137101082*PI*123807~
 PAM*01*1681*ZZ~
 PO4*12~
 PO1**40*CA*56.64**UI*12337004306*UA*135137004306*PI*123375~
 PAM*01*2266*ZZ~
 PO4*16~
 PO1**19*CA*78**UI*12337108318*UA*135137108318*PI*123400~
 PAM*01*1482*ZZ~
 PO4*12~
 CTT*29*1025~ SE*18*179883~
 SE*55*179960~
 GE*38*5850~
 IEA*1*000010952~

850 – DC Purchase Order with Display Item Example v4010:

ISA*00* *00* *ZZ*CVS *01*Supplier ID *130212*1608*U*00401*000010952*0*P*^~
 GS*PO*CVSD*Supplier ID *20130212*1608*5850*X*004010~
 ST*850*179960~
 BEG*00*SA*9999999**20130212~
 REF*VR*19999~
 REF*ZZ**M5~
 PER*BD*KIMBERLEY FELICE DOO~
 SAC*A*F050*ZZ*ZZ**1*.9*****02***OTHER~
 ITD*01*15*2**25**26***100~
 DTM*002*20130313~
 AMT*BAP*4320~
 N9*L1*PO COMMENTS~
 MSG*THIS PO SUBJECT TO THE TERMS AND CONDITIONS FOUND ON CVS SUPPLIERS
 WEBSITE~
 N1*ST**54*Y101~
 N3*ONE CVS DRIVE~
 N4*WAVERLY*NY*14892~
 PO1**75*CA*57.6**PI*999999*UA*099999999999*PI*999999~
 PAM*01*4320*ZZ~
 PID*F****Item Description~
 PO4*1~
 CTT*1*75~
 SE*20*179960~
 GE*38*5850~
 IEA*1*000010952~