

CVS/Caremark

Implementation Guide

812 – DC Credit/Debit Adjustment

Version X12-4010

Table of Contents

812	Credit/Debit Adjustment	1
ISA	Interchange Control Header	2
GS	Functional Group Header	4
ST	Transaction Set Header	6
BCD	Beginning Credit/Debit Adjustment	7
N9	Reference Identification	9
DTM	Date/Time Reference	10
SAC	Service, Promotion, Allowance, or Charge Information	11
N1	Loop Name	13
N1	Name	14
CDD	Loop Credit/Debit Adjustment Detail	16
CDD	Credit/Debit Adjustment Detail	17
LIN	Item Identification	18
PO4	Item Physical Details	20
N9	Reference Identification	20
SE	Transaction Set Trailer	21
GE	Functional Group Trailer	22
IEA	Interchange Control Trailer	23

812

Credit/Debit Adjustment

Functional Group=CD

Purpose: This Draft Standard for Trial Use contains the format and establishes the data contents of the Credit/Debit Adjustment Transaction Set (812) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to notify a trading partner of an adjustment or billback and may be used to request an adjustment or billback. It identifies and contains the details and amounts covering exceptions, adjustments, credits, or debits for goods or services. This transaction set is multi-directional between trading partners.

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	ST	Transaction Set Header	M	1			Must use
020	BCD	Beginning Credit/Debit Adjustment	M	1		N1/020	Must use
040	N9	Reference Identification	O	>1			Used
070	DTM	Date/Time Reference	O	>1			Used
LOOP ID - N1					200		
100	N1	Name	M	1			Must use

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - CDD					>1		
160	CDD	Credit/Debit Adjustment Detail	O	1			Must use
170	LIN	Item Identification	O	1			Used
180	PO4	Item Physical Details	O	1			Used
200	N9	Reference Identification	O	>1			Used
270	SE	Transaction Set Trailer	M	1			Must use

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

Notes:

1/020 BCD05 indicates whether the net of the detail is a credit or a debit.

ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

Purpose: To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier	M	ID	2/2	Must use

Description: Code to identify the type of information in the Authorization Information

CodeList Summary (Total Codes: 7, Included: 1)

<u>Code</u>	<u>Name</u>
00	No Authorization Information Present (No Meaningful Information in I02)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA02	I02	Authorization Information	M	AN	10/10	Must use

Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)

ISA03	I03	Security Information Qualifier	M	ID	2/2	Must use
-------	-----	--------------------------------	---	----	-----	----------

Description: Code to identify the type of information in the Security Information

CodeList Summary (Total Codes: 2, Included: 1)

<u>Code</u>	<u>Name</u>
00	No Security Information Present (No Meaningful Information in I04)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA04	I04	Security Information	M	AN	10/10	Must use

Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)

ISA05	I05	Interchange ID Qualifier	M	ID	2/2	Must use
-------	-----	--------------------------	---	----	-----	----------

Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified

CodeList Summary (Total Codes: 38, Included: 1)

<u>Code</u>	<u>Name</u>
ZZ	Mutually Defined

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA06	I06	Interchange Sender ID	M	AN	15/15	Must use

Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element

ISA07	I05	Interchange ID Qualifier	M	ID	2/2	Must use
-------	-----	--------------------------	---	----	-----	----------

Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified

CodeList Summary (Total Codes: 38, Included: 1)

<u>Code</u>	<u>Name</u>
08	UCC EDI Communications ID (Comm ID)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA08	I07	Interchange Receiver ID	M	AN	15/15	Must use

Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route

data to them

ISA09 I08 **Interchange Date** M DT 6/6 Must use

Description: Date of the interchange

ISA10 I09 **Interchange Time** M TM 4/4 Must use

Description: Time of the interchange

ISA11 I10 **Interchange Control Standards Identifier** M ID 1/1 Must use

Description: Code to identify the agency responsible for the control standard used by the message that is enclosed by the interchange header and trailer

All valid standard codes are used. (Total Codes: 1)

ISA12 I11 **Interchange Control Version Number** M ID 5/5 Must use

Description: Code specifying the version number of the interchange control segments

CodeList Summary (Total Codes: 14, Included: 1)

<u>Code</u>	<u>Name</u>
00401	Draft Standards for Trial Use Approved for Publication by ASC X12 Procedures Review Board through October 1997

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA13	I12	Interchange Control Number	M	N0	9/9	Must use

Description: A control number assigned by the interchange sender

ISA14 I13 **Acknowledgment Requested** M ID 1/1 Must use

Description: Code sent by the sender to request an interchange acknowledgment (TA1)

CodeList Summary (Total Codes: 2, Included: 1)

<u>Code</u>	<u>Name</u>
0	No Acknowledgment Requested

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA15	I14	Usage Indicator	M	ID	1/1	Must use

Description: Code to indicate whether data enclosed by this interchange envelope is test, production or information

CodeList Summary (Total Codes: 3, Included: 1)

<u>Code</u>	<u>Name</u>
T	Test Data

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA16	I15	Component Element Separator	M		1/1	Must use

Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator

GS**Functional Group Header**

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use**Purpose:** To indicate the beginning of a functional group and to provide control information**Element Summary:**

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	Functional Identifier Code	M	ID	2/2	Must use

Description: Code identifying a group of application related transaction sets**CodeList Summary** (Total Codes: 240, Included: 1)

<u>Code</u>	<u>Name</u>
CD	Credit/Debit Adjustment (812)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS02	142	Application Sender's Code	M	AN	2/15	Must use

Description: Code identifying party sending transmission; codes agreed to by trading partners

GS03	124	Application Receiver's Code	M	AN	2/15	Must use
------	-----	------------------------------------	---	----	------	----------

Description: Code identifying party receiving transmission; codes agreed to by trading partners

GS04	373	Date	M	DT	8/8	Must use
------	-----	-------------	---	----	-----	----------

Description: Date expressed as CCYYMMDD

GS05	337	Time	M	TM	4/8	Must use
------	-----	-------------	---	----	-----	----------

Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)

GS06	28	Group Control Number	M	N0	1/9	Must use
------	----	-----------------------------	---	----	-----	----------

Description: Assigned number originated and maintained by the sender

GS07	455	Responsible Agency Code	M	ID	1/2	Must use
------	-----	--------------------------------	---	----	-----	----------

Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480**CodeList Summary** (Total Codes: 2, Included: 1)

<u>Code</u>	<u>Name</u>
X	Accredited Standards Committee X12

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use

Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed**CodeList Summary** (Total Codes: 39, Included: 1)

<u>Code</u>	<u>Name</u>
004010	Draft Standards Approved for Publication by ASC X12 Procedures Review Board through October 1997

Semantics:

1. GS04 is the group date.
2. GS05 is the group time.

3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

Pos: 010	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use

Description: Code uniquely identifying a Transaction Set

CodeList Summary (Total Codes: 298, Included: 1)

<u>Code</u>	<u>Name</u>
812	Credit/Debit Adjustment

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST02	329	Transaction Set Control Number	M	AN	4/9	Must use

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Semantics:

1. The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).

BCD Beginning Credit/Debit Adjustment

Pos: 020	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 10

User Option (Usage): Must use

Purpose: To transmit identifying dates and numbers for the transaction set and indicate the monetary value to the receiver of the transaction

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BCD01	373	Date	M	DT	8/8	Must use
Description: Date expressed as CCYYMMDD						
BCD02	475	Credit/Debit Adjustment Number	M	AN	1/22	Must use
Description: Number assigned by issuer of a credit or debit memo						
BCD03	305	Transaction Handling Code	M	ID	1/2	Must use
Description: Code designating the action to be taken by all parties						
CodeList Summary (Total Codes: 23, Included: 1)						
		<u>Code</u>	<u>Name</u>			
		A	Off Invoice (Deduction from Original Invoice)			
<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BCD04	610	Amount	M	N2	1/15	Must use
Description: Monetary amount						
BCD05	478	Credit/Debit Flag Code	M	ID	1/1	Must use
Description: Code indicating whether amount is a credit or debit						
CodeList Summary (Total Codes: 2, Included: 1)						
		<u>Code</u>	<u>Name</u>			
		C	Credit for CVS			
<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BCD06	373	Date	O	DT	8/8	Must use
Description: Date expressed as CCYYMMDD						
BCD07	76	Invoice Number	X	AN	1/22	Must use
Description: Identifying number assigned by issuer						
BCD09	373	Date	O	DT	8/8	Used
Description: Date expressed as CCYYMMDD						
BCD10	324	Purchase Order Number	X	AN	1/22	Must use
Description: Identifying number for Purchase Order assigned by the orderer/purchaser						
BCD12	640	Transaction Type Code	O	ID	2/2	Must use
Description: Code specifying the type of transaction						
CodeList Summary (Total Codes: 446, Included: 1)						
		<u>Code</u>	<u>Name</u>			
		DR	Debit Memo			

Syntax Rules:

1. R071014 - At least one of BCD07, BCD10 or BCD14 is required.
2. P1314 - If either BCD13 or BCD14 is present, then the other is required.

Semantics:

1. BCD01 is the credit/debit adjustment date.
2. BCD04 is the net amount of this complete transaction.
3. BCD06 is the invoice date.
4. BCD09 is the purchase order date.

Comments:

1. If using BCD07 or BCD10, do not use BCD14 to identify invoice number or purchase order number.
2. For BCD11, only codes 00, 05, 06, 07, and 15 are permitted to be used.

N9 Reference Identification

Pos: 040	Max: >1
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1503, Included: 1)

<u>Code</u>	<u>Name</u>
VR	Vendor ID Number

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N902	127	Reference Identification	X	AN	1/30	Must use

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

Pay Vendor

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

DTM Date/Time Reference

Pos: 070	Max: >1
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Must use
Purpose: To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use

Description: Code specifying type of date or time, or both date and time

CodeList Summary (Total Codes: 1112, Included: 1)

<u>Code</u>	<u>Name</u>
007	Effective

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM02	373	Date	X	DT	8/8	Must use

Description: Date expressed as CCYYMMDD
 Effective Date

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

SAC Service, Promotion, Allowance, or Charge Information

Pos: 097	Max: 25
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To request or identify a service, promotion, allowance, or charge; to specify the amount or percentage for the service, promotion, allowance, or charge

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SAC01	248	Allowance or Charge Indicator	M	ID	1/1	Must use

Description: Code which indicates an allowance or charge for the service specified

CodeList Summary (Total Codes: 7, Included: 1)

<u>Code</u>	<u>Name</u>
A	Allowance

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SAC02	1300	Service, Promotion, Allowance, or Charge Code	X	ID	4/4	Must use

Description: Code identifying the service, promotion, allowance, or charge

CodeList Summary (Total Codes: 1053, Included: 1)

<u>Code</u>	<u>Name</u>
C310	Discount

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SAC05	610	Amount	O	N2	1/15	Must use

Description: Monetary amount

Discount Amount

Syntax Rules:

1. R0203 - At least one of SAC02 or SAC03 is required.
2. P0304 - If either SAC03 or SAC04 is present, then the other is required.
3. P0607 - If either SAC06 or SAC07 is present, then the other is required.
4. P0910 - If either SAC09 or SAC10 is present, then the other is required.
5. C1110 - If SAC11 is present, then SAC10 is required.
6. L130204 - If SAC13 is present, then at least one of SAC02 or SAC04 is required.
7. C1413 - If SAC14 is present, then SAC13 is required.
8. C1615 - If SAC16 is present, then SAC15 is required.

Semantics:

1. If SAC01 is "A" or "C", then at least one of SAC05, SAC07, or SAC08 is required.
2. SAC05 is the total amount for the service, promotion, allowance, or charge.
3. If SAC05 is present with SAC07 or SAC08, then SAC05 takes precedence.
4. SAC08 is the allowance or charge rate per unit.
5. SAC10 and SAC11 is the quantity basis when the allowance or charge quantity is different from the purchase order or invoice quantity.
6. SAC10 and SAC11 used together indicate a quantity range, which could be a dollar amount, that is applicable to service, promotion, allowance, or charge.
7. SAC13 is used in conjunction with SAC02 or SAC04 to provide a specific reference number as identified by the code used.
8. SAC14 is used in conjunction with SAC13 to identify an option when there is more than one option of the promotion.
9. SAC16 is used to identify the language being used in SAC15.

Comments:

1. SAC04 may be used to uniquely identify the service, promotion, allowance, or charge. In addition, it may be used in conjunction to further the code in SAC02.
2. In some business applications, it is necessary to advise the trading partner of the actual dollar amount that a particular allowance, charge, or promotion was based on to reduce ambiguity. This amount is commonly referred to as "Dollar Basis Amount". It is represented in the SAC segment in SAC10 using the qualifier "DO" - Dollars in SAC09.

Loop Name

Pos: 100	Repeat: 200
Mandatory	
Loop: N1	Elements: N/A

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
100	N1	Name	M	1		Must use

N1	Name	Pos: 100	Max: 1
		Heading - Mandatory	
		Loop: N1	Elements: 4

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

CodeList Summary (Total Codes: 1312, Included: 1)

<u>Code</u>	<u>Name</u>
BY	Buying Party (Purchaser)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N102	93	Name	X	AN	1/60	Must use

Description: Free-form name

N103	66	Identification Code Qualifier	X	ID	1/2	Must use
------	----	-------------------------------	---	----	-----	----------

Description: Code designating the system/method of code structure used for Identification Code (67)

CodeList Summary (Total Codes: 215, Included: 1)

<u>Code</u>	<u>Name</u>
1	D-U-N-S Number, Dun & Bradstreet

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N104	67	Identification Code	X	AN	2/80	Must use

Description: Code identifying a party or other code

Duns Number

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

Loop Credit/Debit Adjustment Detail

Pos: 160	Repeat: >1
Optional	
Loop: CDD	Elements: N/A

User Option (Usage): Must use

Purpose: To provide information relative to a line item adjustment

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
160	CDD	Credit/Debit Adjustment Detail	O	1		Must use
170	LIN	Item Identification	O	1		Used
180	PO4	Item Physical Details	O	1		Used
200	N9	Reference Identification	O	>1		Used

CDD Credit/Debit Adjustment Detail

Pos: 160	Max: 1
Detail - Optional	
Loop: CDD	Elements: 8

User Option (Usage): Must use

Purpose: To provide information relative to a line item adjustment

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CDD01	426	Adjustment Reason Code	M	ID	2/2	Must use

Description: Code indicating reason for debit or credit memo or adjustment to invoice, debit or credit memo, or payment

CodeList Summary (Total Codes: 370, Included: 3)

<u>Code</u>	<u>Name</u>
01	Pricing Error
02	Allowance/Charge Error
03	Extension Error
06	Quantity Contested
10	Pallet/Container Charge Error
54	Freight Deducted
55	Tax Deducted
59	Item not received
75	Total Order Not Received

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CDD02	478	Credit/Debit Flag Code	M	ID	1/1	Must use

Description: Code indicating whether amount is a credit or debit

CodeList Summary (Total Codes: 2, Included: 1)

<u>Code</u>	<u>Name</u>
C	Credit
D	Debit

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CDD03	350	Assigned Identification	O	AN	1/20	Must use

Description: Alphanumeric characters assigned for differentiation within a transaction set

CDD04	610	Amount	X	N2	1/15	Must use
-------	-----	--------	---	----	------	----------

Description: Monetary amount

CDD07	477	Credit/Debit Quantity	X	R	1/10	Must use
-------	-----	-----------------------	---	---	------	----------

Description: Number of supplier units credited or debited

CDD08	355	Unit or Basis for Measurement Code	X	ID	2/2	Must use
-------	-----	------------------------------------	---	----	-----	----------

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

CodeList Summary (Total Codes: 794, Included: 1)

<u>Code</u>	<u>Name</u>
PC	Piece

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CDD10	236	Price Identifier Code	X	ID	3/3	Must use

Description: Code identifying pricing specification

CodeList Summary (Total Codes: 164, Included: 1)

<u>Code</u>	<u>Name</u>
-------------	-------------

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CDD11	212	Unit Price	X	R	1/17	Must use
Description: Price per unit of product, service, commodity, etc.						
CDD12	236	Price Identifier Code	X	ID	3/3	Must use
Description: Code identifying pricing specification						
CodeList Summary (Total Codes: 164, Included: 1)						
		<u>Code</u>		<u>Name</u>		
		INV		Invoice Billing Price		
<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CDD13	212	Unit Price	X	R	1/17	Used
Description: Price per unit of product, service, commodity, etc.						

Syntax Rules:

1. R0407 - At least one of CDD04 or CDD07 is required.
2. C0711 - If CDD07 is present, then CDD11 is required.
3. P0708 - If either CDD07 or CDD08 is present, then the other is required.
4. P1011 - If either CDD10 or CDD11 is present, then the other is required.
5. P1213 - If either CDD12 or CDD13 is present, then the other is required.

Semantics:

1. CDD05 is the code indicating whether adjustment is for returned goods. A "Y" confirms that the adjustment is for returned goods.

Comments:

1. If comparison pricing is used, then CDD12 and CDD13 are required.

LIN Item Identification

Pos: 170	Max: 1
Detail - Optional	
Loop: CDD	Elements: 4

User Option (Usage): Must use

Purpose: To specify basic item identification data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
LIN02	235	Product/Service ID Qualifier	M	ID	2/2	Must use

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 477, Included: 1)

<u>Code</u>	<u>Name</u>
PI	Purchaser's Item Code

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
LIN03	234	Product/Service ID	M	AN	1/48	Must use

Description: Identifying number for a product or service
CVS Item Number

LIN04	235	Product/Service ID Qualifier	X	ID	2/2	Must use
-------	-----	------------------------------	---	----	-----	----------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 477, Included: 1)

<u>Code</u>	<u>Name</u>
UI	U.P.C. Consumer Package Code (1-5-5)
ND	If RX – ND (NDC)

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
LIN05	234	Product/Service ID	X	AN	1/48	Must use

Description: Identifying number for a product or service
Item UPC Number
If RX – NDC

Syntax Rules:

1. P0405 - If either LIN04 or LIN05 is present, then the other is required.
2. P0607 - If either LIN06 or LIN07 is present, then the other is required.
3. P0809 - If either LIN08 or LIN09 is present, then the other is required.
4. P1011 - If either LIN10 or LIN11 is present, then the other is required.
5. P1213 - If either LIN12 or LIN13 is present, then the other is required.
6. P1415 - If either LIN14 or LIN15 is present, then the other is required.
7. P1617 - If either LIN16 or LIN17 is present, then the other is required.
8. P1819 - If either LIN18 or LIN19 is present, then the other is required.
9. P2021 - If either LIN20 or LIN21 is present, then the other is required.
10. P2223 - If either LIN22 or LIN23 is present, then the other is required.
11. P2425 - If either LIN24 or LIN25 is present, then the other is required.
12. P2627 - If either LIN26 or LIN27 is present, then the other is required.
13. P2829 - If either LIN28 or LIN29 is present, then the other is required.
14. P3031 - If either LIN30 or LIN31 is present, then the other is required.

Semantics:

1. LIN01 is the line item identification

Comments:

1. See the Data Dictionary for a complete list of IDs.
2. LIN02 through LIN31 provide for fifteen different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

PO4 Item Physical Details

Pos: 180	Max: 1
Detail - Optional	
Loop: CDD	Elements: 1

User Option (Usage): Used

Purpose: To specify the physical qualities, packaging, weights, and dimensions relating to the item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO401	356	Pack	O	N0	1/6	Must use

Description: The number of inner containers, or number of eaches if there are no inner containers, per outer container

Syntax Rules:

1. P0203 - If either PO402 or PO403 is present, then the other is required.
2. C0506 - If PO405 is present, then PO406 is required.
3. P0607 - If either PO406 or PO407 is present, then the other is required.
4. P0809 - If either PO408 or PO409 is present, then the other is required.
5. C1013 - If PO410 is present, then PO413 is required.
6. C1113 - If PO411 is present, then PO413 is required.
7. C1213 - If PO412 is present, then PO413 is required.
8. L13101112 - If PO413 is present, then at least one of PO410, PO411 or PO412 is required.
9. C1716 - If PO417 is present, then PO416 is required.
10. C1804 - If PO418 is present, then PO404 is required.

Semantics:

1. PO415 is used to indicate the relative layer of this package or range of packages within the layers of packaging. Relative Position 1 (value R1) is the innermost package.
2. PO416 is the package identifier or the beginning package identifier in a range of identifiers.
3. PO417 is the ending package identifier in a range of identifiers.
4. PO418 is the number of packages in this layer.

Comments:

1. PO403 - The "Unit or Basis for Measure Code" in this segment position is for purposes of defining the pack (PO401) /size (PO402) measure which indicates the quantity in the inner pack unit. For example: If the carton contains 24 12-Ounce packages, it would be described as follows: Data element 356 = "24"; Data element 357 = "12"; Data element 355 = "OZ".
2. PO413 defines the unit of measure for PO410, PO411, and PO412.

N9

Reference Identification

Pos: 200	Max: >1
Detail - Optional	
Loop: CDD	Elements: 2

User Option (Usage): Must use

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1504, Included: 2)

<u>Code</u>	<u>Name</u>
IA	Internal Vendor Number
ZZ	Mutually Defined

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N902	127	Reference Identification	X	AN	1/30	Must use

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

PO Vendor Number
Item Description

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

SE Transaction Set Trailer

Pos: 270	Max: 1
Detail - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use
		Description: Total number of segments included in a transaction set including ST and SE segments				
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Comments:

1. SE is the last segment of each transaction set.

GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included	M	N0	1/6	Must use
Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element						
GE02	28	Group Control Number	M	N0	1/9	Must use
Description: Assigned number originated and maintained by the sender						

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	Number of Included Functional Groups	M	N0	1/5	Must use
		Description: A count of the number of functional groups included in an interchange				
IEA02	I12	Interchange Control Number	M	N0	9/9	Must use
		Description: A control number assigned by the interchange sender				

812 – Credit/Debit Adjustment Example v4010:

ISA*00* *00* *ZZ*CVS *12*Supplier ID *100426*1700*U*00400*000006035*0*P*^~
 GS*CD*CVS*Supplier ID*20100426*1700*4*X*004010~
 ST*812*0005~
 BCD*20100409*999999999V*A*146201*C*20100104*999999999**20091224*8293673**DR~
 N9*VR*19999~
 DTM*007*20100404~
 SAC*A****2983~
 N1*BY*CVS/PHARMACY*1*001786664~
 CDD*06*C*00001*149184***336*PC**OPP*9.99*INV*9.99~
 LIN**PT*027136*UI*0009999999999~
 N9*IA*19999~
 N9*ZZ*Item Description~
 SE*11*0005~
 GE*1*4~
 IEA*1*000006035~